

EZPull MT-8 User Guide

EZPull MT-8 is a waterproof, wireless, transmitter for 8 traps. Model MT-8_Pro is wireless remote for EZPull TargetManager target counter card reader.

Releasing Targets

1. Singles: press and release any key 1-8. The "T1" LED lights up momentarily.
2. True Pair: Press the Target [🎯] key. The "S" LED will flash rapidly. Select the first traps using keys 1-8. The "T1" LED lights up and the "S" LED blinks slower. Select the second trap using keys 1-8. The "T2" LED lights up and the "S" LED blinks very slowly indicating both targets selected. When the shooter calls "pull", press the Target [🎯] key again to release the targets.
It is also possible to select a True Pair by pressing two buttons simultaneously.
3. Rafael Pair: Repeat steps from True Pair but select the same trap twice. Press the Target [🎯] key again to release the first target. The second target will automatically follow in approximately 2.4 seconds.



Solo Delay

The standalone model MT-8 (*) can be programmed for Solo Delay between 2 and 4 seconds (see MT-8 Setup Guide).

4. Singles, True Pair and Rafael Pair are operated as per Manual Mode sections 1 to 3. The target(s) will be release "Solo Delay" seconds after pressing the button(s).
5. Report Pair: Select the first trap. The "T1" LED lights up. Immediately select the second trap. The "T2" LED lights up. The first target will be delayed between 2 and 4 seconds depending on the "Solo Delay" setup value. The second target will be delayed between 1 and 4 seconds depending on the "following pair delay" setup value.

(*) For MT-8_Pro, the solo delay is set by the TargetManager card reader.